


Wskaźnik dostrojenia

EM 81


Philips

Nowal



$$U_z = 6.3 \text{ V}$$

$$I_z = 300 \text{ mA}$$



Wartości robocze

| | | | |
|----------|------|------------|----|
| U_{ab} | 250 | V | |
| U_L | 250 | V | |
| R_a | 0,5 | M Ω | |
| R_s | 3 | M Ω | |
| U_s | -1 | V | |
| α | 65° | 5° | |
| I_a | 0,37 | 0,02 | mA |
| I_L | 2,0 | 2,3 | mA |

Wartości graniczne

| | | |
|--------------|--------------------|------------|
| U_{a0max} | 550 | V |
| U_{amax} | 300 | V |
| P_{amax} | 0,2 | W |
| U_{L0max} | 550 | V |
| U_{Lmax} | 300 | V |
| U_{Lmin} | 165 | V |
| I_{kmax} | 3 | mA |
| $U_{w/kmax}$ | 100 | V |
| U_{smax} | -1,3 ¹⁾ | V |
| R_{smax} | 3 | M Ω |
| $R_{w/kmax}$ | 20 | k Ω |

¹⁾ $I_s = +0,3 \mu\text{A}$

TYPY PODOBNE

6 DA 5

