# AMERICAN STANDARD SERIES

# ALPHA 3-8

The Eminence Alpha 3-8 is a truly versatile compact full-range driver perfectly suited for tight fitting pro audio line array and column array applications. With a program power rating of 60 watts, this 3" driver utilizes an 8.3 oz ferrite magnet in conjunction with an internal neodymium bucking magnet for increased sensitivity and extends the response out to 20kHz. The highly pressed cone sandwiches paper with a layer of water-resistant polypropylene for increased stiffness and lower distortion.

- 60 W Program Power
- 3.0" Nominal Diameter
- 8 n

APPLICATION		ENCLOSURE	
Full range	v	Sealed Box	V
Midrange	V	Vented Box	~
Midbass		Scoop Loading	
Woofer		Horn Loading	
Subwoofer			
		!	

### SPECIFICATION

Nominal Basket Diameter	3.0″, 76 mm 8 Ω		
Nominal Impedance*			
Power Rating*			
Program Power	60 W		
Nominal Power	30 W		
Resonance	118 Hz		
Usable Frequency Range	150 Hz – 20.0 kHz		
Sensitivity*	88.6 dB		
Magnet Weight	8 oz.		
Gap Height	0.10", 2.5 mm		
Voice Coil Diameter	0.787", 20 mm		

## MATERIALS OF CONSTRUCTION

Copper voice coil
Polyimide former
Ferrite magnet
Vented / Flux source cap
Pressed steel basket
Paper/Poly sandwich cone
Poly cone edge
Poly dust cap



#### THIELE & SMALL PARAMETERS

ES


#### MOUNTING INFORMATION

Recommended Enclosure Volume

1.3	110112	Necommended Enclosure volume	
Re	5.12 Ω	Sealed	0.85-1.42 liters,
Le	0.11 mH		0.03-0.05 cu.ft.
Qms	7.94	Vented	1.42-1.98 liters,
Qes	0.53		0.05-0.07 cu.ft.
Qts	0.50	Driver Volume Displaced	0.005 cu.ft., 0.13 liters
Vas	0.03 cu.ft., 0.95 liters	Major Diameter	3.98", 101.1 mm
Vd	6.9 cc	Flat to Flat Diameter	3.24", 82.3 mm
Cms	0.84 mm/N	Baffle Hole Diameter	3.04", 77.2 mm
BL	3.93 T-M	Front Sealing Gasket	Yes
Mms	2 grams	Rear Sealing Gasket	Yes
EBP	220	Mounting Holes Diameter	0.16", 4.1 mm
Xmax	2.40 mm	Mounting Holes B.C.D.	3.63", 92.1 mm
Sd	28.6 cm2	Depth	1.76 <u>",</u> 44.6 mm
Xlim	4.0 mm	Net Weight	0.90 lbs , 0.41 kg
		Shipping Weight	1.10 lbs , 0.50 kg

118 Hz

### FREQUENCY RESPONSE & IMPEDANCE CURVE



See footnotes on page 155 for information regarding usable frequency range, nominal impedance, power rating and sensitivity.