

Wskaźnik elektronowy


6 BR 5

Wskaźnik dostrojenia

Nowal



$U_z = 6,3V$
 $I_z = 0,3A$ k,s



Wartości robocze

U_{ab}	200	250	V
U_{eb}	200	250	V
U_s	0... -16	0... -20	V
I_a	380... 40	480... 50	μA
I_e	1,5... 2,7	2... 3,6	mA
R_a	0,5	0,5	M Ω
$\alpha^1)$	0... 26	0... 26	mm

Wartości maksymalne

U_{amax}	300	V
P_{amax}	0,2	W
U_{emax}	300	V
R_{smax}	3	M Ω
U_{wlkmax}	100	V

¹⁾ Łuk kąta świecącego w mm.

TYPY PODOBNE

EM 80