
3959

DMOS FULL-BRIDGE PWM MOTOR DRIVER



Note that the A3959SLB(SOIC), A3959SB (DIP), and A3959SLP (TSSOP) do <u>not</u> share a common terminal assignment.

ABSOLUTE MAXIMUM RATINGS

Load Supply Voltage, V _{BB} 50 V
Output Current, I _{OUT} (Repetitive) ±3.0 A
(Peak, <3 μs) ± 6.0 A
Logic Supply Voltage, V _{DD} 7.0 V
Logic Input Voltage Range, V _{IN}
(Continuous)0.3 V to V _{DD} + 0.3 V
(t _w <30 ns) -1.0 V to V_{DD} + 1.0 V
Sense Voltage, V _S (Continuous) 0.5 V
(t _w <3 μs) 2.5 V
Reference Voltage, V_{REF}
Package Power Dissipation ($T_A = 25^{\circ}C$), P_D
A3959SB 3.3 W*
A3959SLB 2.5 W*
A3959SLP 3.1 W*
Operating Temp. Range, T _A 20°C to +85°C
Junction Temperature, T _J +150°C
Storage Temp. Range, $T_S \ldots \ldots$ -55°C to +150°C
Output current rating may be limited by duty cycle, ambient temperature, and heat sinking. Under any set of conditions, do not exceed the specified current rating or a junction temperature of 150°C.

Designed for pulse-width modulated (PWM) current control of dc motors, the A3959SB, A3959SLB, and A3959SLP are capable of output currents to ± 3 A and operating voltages to 50 V. Internal fixed off-time PWM current-control timing circuitry can be adjusted via control inputs to operate in slow, fast, and mixed current-decay modes.

PHASE and ENABLE input terminals are provided for use in controlling the speed and direction of a dc motor with externally applied PWM-control signals. Internal synchronous rectification control circuitry is provided to reduce power dissipation during PWM operation.

Internal circuit protection includes thermal shutdown with hysteresis, undervoltage monitoring of supply and charge pump, and crossover-current protection. Special power-up sequencing is not required.

The A3959SB/SLB/SLP is a choice of three power packages, a 24-pin plastic DIP with a copper batwing tab (package suffix 'B'), a 24-lead plastic SOIC with a copper batwing tab (package suffix 'LB'), and a thin (<1.2 mm) 28-lead plastic TSSOP with an exposed thermal pad (suffix 'LP'). In all cases, the power tab is at ground potential and needs no electrical isolation.

FEATURES


- ±3 A, 50 V Output Rating
 - Low $r_{DS(on)}$ Outputs (270 m Ω , Typical)
- Mixed, Fast, and Slow Current-Decay Modes
- Synchronous Rectification for Low Power Dissipation
- Internal UVLO and Thermal-Shutdown Circuitry
- Crossover-Current Protection
- Internal Oscillator for Digital PWM Timing

Always order by complete part number:

Part Number	Package	R _{θJA} *	R _{θJT}
A3959SB	24-pin batwing DIP	38°C/W	6°C/W
A3959SLB	24-lead batwing SOIC	50°C/W	6°C/W
A3959SLP	28-lead thin shrink SOIC	40°C/W	—

* Double-sided board, one square inch copper each side. See also, Layout, page 7







115 Northeast Cutoff, Box 15036 Worcester, Massachusetts 01615-0036 (508) 853-5000 Copyright © 2001, 2003 Allegro MicroSystems, Inc.

ELECTRICAL CHARACTERISTICS at T_A = +25°C, V_{BB} = 50 V, V_{DD} = 5.0 V, V_{SENSE} = 0.5 V, f_{PWM} < 50 kHz (unless noted otherwise)

	Limits		nits			
Characteristics	Symbol	Test Conditions	Min.	Тур.	Max.	Units
Output Drivers		-				-
Load Supply Voltage Range	V _{BB}	Operating	9.5	_	50	V
		During sleep mode	0	_	50	V
Output Leakage Current	I _{DSS}	V _{OUT} = V _{BB}	_	<1.0	20	μA
		V _{OUT} = 0 V	_	<-1.0	-20	μA
Output On Resistance	r _{DS(on)}	Source driver, I _{OUT} = -3 A	_	270	300	mΩ
		Sink driver, I _{OUT} = 3 A	_	270	300	mΩ
Crossover Delay			300	600	1000	ns
Body Diode Forward Voltage	V _F	Source diode, I _F = -3 A	_	_	1.6	V
		Sink diode, I _F = 3 A	_	_	1.6	V
Load Supply Current	I _{BB}	f _{PWM} < 50 kHz	_	4.0	7.0	mA
		Charge pump on, outputs disabled	_	2.0	5.0	mA
		Sleep Mode	_	_	20	μA
Control Logic						
Logic Supply Voltage Range	V _{DD}	Operating	4.5	5.0	5.5	V
Logic Input Voltage	V _{IN(1)}		2.0	_	-	V
	V _{IN(0)}		_	_	0.8	V
Logic Input Current	I _{IN(1)}	V _{IN} = 2.0 V	_	<1.0	20	μA
(all inputs except ENABLE)	I _{IN(0)}	V _{IN} = 0.8 V	_	<-2.0	-20	μA
ENABLE Input Current	I _{IN(1)}	V _{IN} = 2.0 V	_	40	100	μA
	I _{IN(0)}	V _{IN} = 0.8 V	_	16	40	μA
Internal OSC frequency	f _{OSC}	R _{OSC} shorted to GROUND	3.25	4.25	5.25	MHz
		$R_{OSC} = 51 \text{ k}\Omega$	3.65	4.25	4.85	MHz
Reference Input Volt. Range	V _{REF}	Operating	0.0	_	V_{DD}	V
Reference Input Current	I _{REF}	$V_{REF} = V_{DD}$	_	_	±1.0	μA
Comparator Input Offset Volt.	V _{IO}	V _{REF} = 0 V	_	±5.0	_	mV

Continued next page ...

ELECTRICAL CHARACTERISTICS at $T_A = +25^{\circ}C$, $V_{BB} = 50$ V, $V_{DD} = 5.0$ V, $V_{SENSE} = 0.5$ V, $f_{PWM} < 50$ kHz (unless noted otherwise), continued.

				Lir	nits	
Characteristics	Symbol	Test Conditions	Min.	Тур.	Max.	Units
Control Logic						-
Reference Divider Ratio	_		Ι	10	_	-
G _m Error	E_{Gm}	$V_{REF} = V_{DD}$	-	_	±4.0	%
(Note 3)		V _{REF} = 0.5 V	-	_	±14	%
Propagation Delay Times	t _{pd}	0.5 E _{in} to 0.9 E _{out} : PWM change to source on PWM change to source off PWM change to sink on PWM change to sink off	600 50 600 50	750 150 750 100	1200 350 1200 150	ns ns ns ns
Thermal Shutdown Temp.	Т _Ј		Ι	165	_	°C
Thermal Shutdown Hysteresis	ΔT_{J}		Ι	15	_	°C
UVLO Enable Threshold	UVLO	Increasing V _{DD}	3.90	4.2	4.45	V
UVLO Hysteresis	∆UVLO		0.05	0.10	_	V
Logic Supply Current	I _{DD}	f _{PWM} < 50 kHz	_	6.0	10	mA
		Sleep Mode	_	_	2.0	mA

NOTES: 1. Typical Data is for design information only.

- 2. Negative current is defined as coming out of (sourcing) the specified device terminal.
- 3. $G_{m} \operatorname{error} = ([V_{REF}/10] V_{SENSE})/(V_{REF}/10)$ where $V_{SENSE} = I_{TRIP} \cdot R_{S}$.



FUNCTIONAL DESCRIPTION

 V_{REG} . This internally generated voltage is used to operate the sink-side DMOS outputs. The V_{REG} terminal should be decoupled with a 0.22 µF capacitor to ground. V_{REG} is internally monitored and in the case of a fault condition, the outputs of the device are disabled.

Charge Pump. The charge pump is used to generate a gate-supply voltage greater than V_{BB} to drive the sourceside DMOS gates. A 0.22 μ F ceramic capacitor should be connected between CP1 and CP2 for pumping purposes. A 0.22 μ F ceramic capacitor should be connected between CP and V_{BB} to act as a reservoir to operate the high-side DMOS devices. The CP voltage is internally monitored and, in the case of a fault condition, the source outputs of the device are disabled.

PHASE Logic. The PHASE input terminal determines if the device is operating in the "forward" or "reverse" state.

PHASE	OUT _A	OUT _B	
0	Low	High	
1	High	Low	

ENABLE Logic. The ENABLE input terminal allows external PWM. ENABLE high turns on the selected sink-source pair. ENABLE low switches off the source driver or the source and sink driver, depending on EXT MODE, and the load current decays. If ENABLE is kept high, the current will rise until it reaches the level set by the internal current-control circuit.

ENABLE	Outputs
0	Chopped
1	On

EXT MODE Logic. When using external PWM current control, the EXT MODE input determines the current path during the chopped cycle. With EXT MODE low, fast decay mode, the opposite pair of selected outputs will be enabled during the off cycle. With EXT MODE high, slow decay mode, both sink drivers are on with ENABLE low.

EXT MODE	Decay	
0	Fast	
1	Slow	

Current Regulation. Load current is regulated by an internal fixed off-time PWM control circuit. When the outputs of the DMOS H bridge are turned on, the current increases in the motor winding until it reaches a trip value determined by the external sense resistor (R_S) and the applied analog reference voltage (V_{REF}):

$$I_{TRIP} = V_{REF} / 10R_S$$

At the trip point, the sense comparator resets the sourceenable latch, turning off the source driver. The load inductance then causes the current to recirculate for the fixed off-time period. The current path during recirculation is determined by the configuration of slow/ mixed/fast current-decay mode via PFD1 and PFD2.

Oscillator. The PWM timer is based on an internal oscillator set by a resistor connected from the R_{OSC} terminal to V_{DD} . Typical value of 4 MHz is set with a 51 k Ω resistor. The allowable range of the resistor is from 20 k Ω to 100 k Ω .

$$f_{OSC} = 204 \text{ x } 10^9/R_{OSC}.$$

If R_{OSC} is not pulled up to V_{DD} , it must be shorted to ground.

Fixed Off Time. The A3959 is set for a fixed off time of 96 cycles of the internal oscillator, typically 24 μ s with a 4 MHz oscillator.

FUNCTIONAL DESCRIPTION (continued)

Internal Current-Control Mode. Inputs PFD1 and PFD2 determine the current-decay method after an overcurrent event is detected at the SENSE input. In slow-decay mode, both sink drivers are turned on for the fixed off-time period. Mixed-decay mode starts out in fast-decay mode for a portion (15% or 48%) of the fixed off time, and then is followed by slow decay for the remainder of the period.

PFD2	PFD1	% t _{off}	Decay
0	0	0	Slow
0	1	15	Mixed
1	0	48	Mixed
1	1	100	Fast

PWM Blank Timer. When a source driver turns on, a current spike occurs due to the reverse-recovery currents of the clamp diodes and/or switching transients related to distributed capacitance in the load. To prevent this current spike from erroneously resetting the source-enable latch, the sense comparator is blanked. The blank timer runs after the off-time counter to provide the blanking function. The blank timer is reset when ENABLE is chopped or PHASE is changed. For external PWM control, a PHASE change or ENABLE on will trigger the blanking function. The duration is determined by the BLANK input and the oscilator.

BLANK	t _{blank}	
0	6/f _{osc}	
1	12/f _{osc}	

Synchronous Rectification. When a PWM off cycle is triggered, either by an ENABLE chop command or internal fixed off-time cycle, load current will recirculate according to the decay mode selected by the control logic. The A3959 synchronous rectification feature will turn on the appropriate pair of DMOS outputs during the current decay and effectively short out the body diodes with the low $r_{DS(on)}$ driver. This will reduce power dissipation significantly and can eliminate the need for external Schottky diodes.

Synchronous rectification will prevent reversal of load current by turning off all outputs when a zero-current level is detected.

Shutdown. In the event of a fault (excessive junction temperature, or low voltage on CP or V_{REG}) the outputs of the device are disabled until the fault condition is removed. At power up, and in the event of low V_{DD} , the UVLO circuit disables the drivers.

Braking. The braking function is implemented by driving the device in slow-decay mode via EXTMODE and applying an enable chop command. Because it is possible to drive current in either direction through the DMOS drivers, this configuration effectively shorts out the motor-generated BEMF as long as the ENABLE chop mode is asserted. It is important to note that the internal PWM current-control circuit will not limit the current when braking, because the current does not flow through the sense resistor. The maximum brake current can be approximated by V_{BEMF}/R_L . Care should be taken to ensure that the maximum ratings of the device are not exceeded in worst-case braking situations of high speed and high inertial loads.

SLEEP Logic. The SLEEP input terminal is used to minimize power consumption when when not in use. This disables much of the internal circuitry including the regulator and charge pump. Logic low will put the device into sleep mode, logic high will allow normal operation.




FUNCTIONAL DESCRIPTION (continued)

Current Sensing. To minimize inaccuracies in sensing the I_{TRIP} current level, which may be caused by ground trace IR drops, the sense resistor should have an independent ground return to the ground terminal of the device. For low-value sense resistors the IR drops in the PCB sense resistor's traces can be significant and should be taken into account. The use of sockets should be avoided as they can introduce variation in R_S due to their contact resistance.

The maximum value of R_S is given as $R_S \le 0.5/I_{TRIP}$ where $I_{TRIP} \le 3.0$ A.

Thermal Protection. Circuitry turns off all drivers when the junction temperature reaches 165°C typically. It is intended only to protect the device from failures due to excessive junction temperatures and should not imply that output short circuits are permitted. Thermal shutdown has a hysteresis of approximately 15°C.



Dwg. GP-049-6

Layout. A star ground system located close to the driver is recommended. The printed wiring board should use a heavy ground plane. For optimum electrical and thermal performance*, the driver should be soldered directly onto the board. The ground side of R_S should have an individual path to the ground terminals of the device. This path should be as short as is possible physically and should not have any other components connected to it. It is recommended that a 0.1 μ F capacitor be placed between SENSE and ground as close to the device as possible; the load supply terminal, V_{BB} , should be decoupled with an electrolytic capacitor (> 47 μ F is recommended) placed as close to the device as is possible. On the 28-lead TSSOP package, the copper ground plane located under the exposed thermal pad is typically used as a star ground.

* The thermal resistance, $R_{\theta JA}$, and absolute maximum allowable package power dissipation specified on page 1 is measured on a typical two-sided PCB with one square inch copper ground area on each side. With minimal copper on a single-sided PCB (worst-case), the 'B' package $R_{\theta JA}$ is 40°C/W, 'LB' is 77°C/W, and 'LP' is 80°C/W. See also, Application Note 29501.5, *Improving Batwing Power Dissipation*.

For specification purposes, the multi-layer high-K board performance graphed here is per JEDEC Standard JESD51.

The products described here are manufactured under one or more U.S. patents or U.S. patents pending.

Allegro MicroSystems, Inc. reserves the right to make, from time to time, such departures from the detail specifications as may be required to permit improvements in the performance, reliability, or manufacturability of its products. Before placing an order, the user is cautioned to verify that the information being relied upon is current.

Allegro products are not authorized for use as critical components in life-support devices or systems without express written approval.

The information included herein is believed to be accurate and reliable. However, Allegro MicroSystems, Inc. assumes no responsibility for its use; nor for any infringement of patents or other rights of third parties which may result from its use.


Terminal List

		LB	В	LP
Terminal Name	Terminal Description	(SOIC)	(DIP)	(TSSOP)
СР	Reservoir capacitor (typically 0.22 µF)	1	24	1
CP1 & CP2	The charge pump capacitor (typically 0.22 μ F)	2&3	1 & 2	2&3
NC	No (internal) connection	—		4
PHASE	Logic input for direction control	4	3	5
ROSC	Oscillator resistor	5	4	6
GROUND	Grounds	6, 7	5, 6, 7, 8	* 7, 8*
LOGIC SUPPLY	V_{DD} , the low voltage (typically 5 V) supply	8	9	9
ENABLE	Logic input for enable control	9	10	10
NC	No (internal) connection	-	_	11
PFD2	Logic-level input for fast decay	10	11	12
BLANK	Logic-level input for blanking control	11	12	13
PFD1	Logic-level input for fast decay	12	13	14
REF	V _{REF} , the load current reference input voltage	13	14	15
EXT MODE	Logic input for PWM mode control	14	15	16
NO CONNECT	No (Internal) connection	15		17
OUT _A	One of two DMOS bridge outputs to the motor	16	16	18
NC	No (internal) connection	-	_	19, 20
SENSE	Sense resistor	17	17	21
NC	No (internal) connection	-	_	22
GROUND	Grounds	18, 19	18, 19*	_
LOAD SUPPLY	V_{BB} , the high-current, 9.5 V to 50 V, motor supply	20	20	23
OUT _B	One of two DMOS bridge outputs to the motor	21	21	24
NO CONNECT	No (Internal) connection	22		25
SLEEP	Logic-level Input for sleep operation	23	22	26
V _{REG}	Regulator decoupling capacitor (typically 0.22 μ F)	24	23	27
GROUND	Ground			28*

* For the A3959SB (DIP) only, there is an indeterminate resistance between the substrate grounds (pins 6, 7, 18, and 19) and the grounds at pins 5 and 8. Pins 5 and 8, and 6, 7, 18, or 19 must be connected together externally. For the A3959SLP (TSSOP) the grounds at terminals 7, 8, and 28 should be connected together at the exposed pad beneath the device.



115 Northeast Cutoff, Box 15036 Worcester, Massachusetts 01615-0036 (508) 853-5000



A3959SB

Dimensions in Inches (controlling dimensions)

NOTES: 1. Webbed lead frame. Leads 6, 7, 18, and 19 are internally one piece.

- 2. Exact body and lead configuration at vendor's option within limits shown.
- 3. Lead spacing tolerance is non-cumulative.
- 4. Lead thickness is measured at seating plane or below.
- 5. Supplied in standard sticks/tubes of 15 devices.

A3959SLB 24 13 0.0125 0.0091 Р Γ **Dimensions in Inches** 0.419 0.394 0.2992 0.2914 (for reference only) 0.050 0.016 Н H Ħ F 0.020 0.013 ĪI 2 3 0.050 0° TO 8° 0.6141 BSC 0.5985 NOTE 1 NOTE 3 0.0926 0.1043 L 0.0040 MIN. Dwg. MA-008-25A in 24 0.32 0.23 10.65 10.00 7.60 7.40 **Dimensions in Millimeters** (controlling dimensions) 1.27 0.40 Н Н H Н H ŧ 0.51 0.33 2 3 1.27 BSC 15.60 15.20 0° to 8° NOTE 1 NOTE 3 2.65 2.35

NOTES: 1. Exact body and lead configuration at vendor's option within limits shown.

2. Lead spacing tolerance is non-cumulative.

0.10 MIN.


L

- 3. Webbed lead frame. Leads 6, 7, 18, and 19 are internally one piece.
- 4. Supplied in standard sticks/tubes of 31 devices or add "TR" to part number for tape and reel.



115 Northeast Cutoff, Box 15036 Worcester, Massachusetts 01615-0036 (508) 853-5000

Dwg. MA-008-25A mm



NOTES: 1. Exact body and lead configuration at vendor's option within limits shown.

- 2. Lead spacing tolerance is non-cumulative.
- 3. Supplied in standard sticks/tubes of 49 devices or add "TR" to part number for tape and reel.

MOTOR DRIVERS

INTEGRATED CIRCUITS FOR BRUSHLESS DC MOTORS 3-Phase Power MOSFET Controller — 28 V 3933 3-Phase Power MOSFET Controller — 40 V 3935 3-Phase Power MOSFET Controller — 50 V 3932 & 3938 3-Phase Back-EMF Controller/Driver ±900 mA 14 V 8904 3-Phase PWW Current-Controlled DMOS Driver ±3.0 A 50 V 3936 INTEGRATED BRIDGE DRIVERS FOR DC AND BIPOLAR STEPPER MOTORS PUM Current-Controlled Dual Full Bridge ±500 mA 18 V 3965 Dual Full Bridge with Protection & Diagnostics ±500 mA 30 V 3966 PWM Current-Controlled Dual Full Bridge ±750 mA 45 V 2916 PWM Current-Controlled Dual Full Bridge ±750 mA 45 V 2919 PWM Current-Controlled Dual Full Bridge ±10 A 35 V 3963 PWM Current-Controlled Dual Full Bridge ±1.5 A 45 V 2917 PWM Current-Controlled Dual Full Bridge ±1.5 A 50 V 3948 PWM Current-Controlled Dual Full Bridge ±1.5 A 50 V 3955 <	Function	Output R	-	Part Number [†]
3-Phase Power MOSFET Controller — 40 V 3935 3-Phase Power MOSFET Controller — 50 V 3932 & 3938 3-Phase Back-EMF Controller/Driver ±900 mA 14 V 8904 3-Phase PWM Current-Controlled DMOS Driver ±3.0 A 50 V 3936 INTEGRATED BRIDGE DRIVERS FOR DC AND BIPOLAR STEPPER MOTORS PWM Current-Controlled Dual Full Bridge ±500 mA 30 V 3966 Dual Full Bridge with Protection & Diagnostics ±500 mA 30 V 3966 PWM Current-Controlled Dual Full Bridge ±750 mA 30 V 3966 PWM Current-Controlled Dual Full Bridge ±750 mA 30 V 3967 PWM Current-Controlled Dual Full Bridge ±750 mA 45 V 2916 PWM Current-Controlled Dual Full Bridge ±750 mA 45 V 2919 PWM Current-Controlled Dual Full Bridge ±1.0 A 35 V 3973 PWM Current-Controlled Dual Full Bridge ±1.5 A 45 V 2917 PWM Current-Controlled Dual Full Bridge ±1.5 A 50 V 3933 PWM Current-Controlled Dual Full Bridge ±1.5 A 50 V 3948 PWM Current-	INTEGRATED CIRCUITS	FOR BRUSHLE	ESS DC MOTO	RS
3-Phase Power MOSFET Controller // 07/94 - 50 V 3932 & 3938 3-Phase Back-EMF Controller/Driver ±900 mA 14 V 8904 3-Phase PWM Current-Controlled DNOS Driver ±3.0 A 50 V 3936 INTEGRATED BRIDCE DRIVERS FOR DC AND BIPOLAR STEPPER MOTORS PWM Current-Controlled Dual Full Bridge ±650 mA 30 V 3966 PWM Current-Controlled Dual Full Bridge ±650 mA 30 V 3966 PWM Current-Controlled Dual Full Bridge ±750 mA 30 V 3967 PWM Current-Controlled Dual Full Bridge ±750 mA 45 V 2919 PWM Current-Controlled Dual Full Bridge ±750 mA 45 V 2919 PWM Current-Controlled Dual Full Bridge ±750 mA 45 V 2919 PWM Current-Controlled Dual Full Bridge ±1.0 A 35 V 3973 PWM Current-Controlled Dual Full Bridge ±1.5 A 50 V 3953 PWM Current-Controlled Dual Full Bridge ±1.5 A 50 V 3973 PWM Current-Controlled Dual Full Bridge ±1.5 A 50 V 3973 PWM Current-Controlled Dual Full Br	3-Phase Power MOSFET Controller		28 V	3933
3-Phase Back-EMF Controller/Driver ±900 mA 14 V 8904 3-Phase PWM Current-Controlled DMOS Driver ±3.0 A 50 V 3936 INTEGRATED BRIDGE DRIVERS FOR DC AND BIPOLAR STEPPER MOTORS PWM Current-Controlled Dual Full Bridge ±500 mA 30 V 3965 Dual Full Bridge DI Full Bridge ±650 mA 30 V 3966 PWM Current-Controlled Dual Full Bridge ±750 mA 30 V 3967 PWM Current-Controlled Dual Full Bridge ±750 mA 45 V 2916 PWM Current-Controlled Dual Full Bridge ±750 mA 45 V 2919 PWM Current-Controlled Dual Full Bridge ±750 mA 45 V 2919 PWM Current-Controlled Dual Full Bridge ±1.0 A 35 V 3964 PWM Current-Controlled Dual Full Bridge ±1.5 A 50 V 3953 PWM Current-Controlled Dual Full Bridge ±1.5 A 50 V 3955 PWM Current-Controlled Dual Full Bridge ±1.5 A 50 V 3955 PWM Current-Controlled Microstepping Full Bridge ±1.5 A 50 V 3957 PWM Current-C	3-Phase Power MOSFET Controller	_	40 V	3935
3-Phase PWM Current-Controlled DMOS Driver±3.0 A50 V3936INTEGRATED BRIDGE DRIVERS FOR DC AND BIPOLAR STEPPER MOTORSPWM Current-Controlled Dual Full Bridge±500 mA30 V3965Dual Full Bridge with Protection & Diagnostics±500 mA30 V3966PWM Current-Controlled Dual Full Bridge±650 mA30 V3968Microstepping Translator/Dual Full Bridge±750 mA30 V3967PWM Current-Controlled Dual Full Bridge±750 mA45 V2916PWM Current-Controlled Dual Full Bridge±750 mA45 V2919PWM Current-Controlled Dual Full Bridge±750 mA45 V2919PWM Current-Controlled Dual Full Bridge±10 A35 V3973PWM Current-Controlled Dual Full Bridge±1.0 A35 V3973PWM Current-Controlled Dual Full Bridge±1.5 A50 V3953PWM Current-Controlled Dual Full Bridge±1.5 A50 V3953PWM Current-Controlled Dual Full Bridge±1.5 A50 V3955PWM Current-Controlled Microstepping Full Bridge±1.5 A50 V3957PWM Current-Controlled Microstepping Full Bridge±1.5 A50 V3957PWM Current-Controlled Dual DMOS Full Bridge±1.5 A50 V3958PWM Current-Controlled	3-Phase Power MOSFET Controller	_	50 V	3932 & 3938
INTEGRATED BRIDGE DRIVERS FOR DC AND BIPOLAR STEPPER MOTORSPWM Current-Controlled Dual Full Bridge±500 mA18 V3965Dual Full Bridge with Protection & Diagnostics±500 mA30 V3976PWM Current-Controlled Dual Full Bridge±650 mA30 V3968Microstepping Translator/Dual Full Bridge±750 mA30 V3967PWM Current-Controlled Dual Full Bridge±750 mA45 V2916PWM Current-Controlled Dual Full Bridge±750 mA45 V2919PWM Current-Controlled Dual Full Bridge±750 mA45 V2919PWM Current-Controlled Dual Full Bridge±10 mA33 V3964PWM Current-Controlled Dual Full Bridge±1.0 A35 V3973PWM Current-Controlled Dual Full Bridge±1.1 A50 V3953PWM Current-Controlled Dual Bridge±1.5 A50 V3948PWM Current-Controlled Dual Full Bridge±1.5 A50 V3957PWM Current-Controlled Microstepping Full Bridge±1.5 A50 V3972PWM Current-Controlled Microstepping Full Bridge±1.5 A50 V3972PWM Current-Controlled Dual DMOS Full Bridge±1.5 A50 V3973PWM Current-Controlled Dual DMOS Full Bridge±1.5 A50 V3974PWM Current-Controlled Dual DMOS Full Bridge±1.5 A50 V3974PWM Current-Controlled Dual DMOS Full Bridge±1.5 A50 V3977PWM Current-Controlled Dual DMOS Full Bridge±1.5 A50 V3976PUM Current-Controlled DM	3-Phase Back-EMF Controller/Driver	±900 mA	14 V	8904
PWM Current-Controlled Dual Full Bridge ±500 mA 18 V 3965 Dual Full Bridge with Protection & Diagnostics ±500 mA 30 V 3976 PWM Current-Controlled Dual Full Bridge ±650 mA 30 V 3966 PWM Current-Controlled Dual Full Bridge ±650 mA 30 V 3967 PWM Current-Controlled Dual Full Bridge ±750 mA 45 V 2916 PWM Current-Controlled Dual Full Bridge ±750 mA 45 V 2919 PWM Current-Controlled Dual Full Bridge ±750 mA 45 V 2919 PWM Current-Controlled Dual Full Bridge ±750 mA 45 V 2919 PWM Current-Controlled Dual Full Bridge ±10 A 35 V 3964 PWM Current-Controlled Dual Full Bridge ±1.3 A 50 V 3953 PWM Current-Controlled Dual Full Bridge ±1.5 A 50 V 3948 PWM Current-Controlled Microstepping Full Bridge ±1.5 A 50 V 3957 PWM Current-Controlled Microstepping Full Bridge ±1.5 A 50 V 3957 PWM Current-Controlled Microstepping Full Bridge ±1.5 A 50 V 3958 <td>3-Phase PWM Current-Controlled DMOS Driver</td> <td>±3.0 A</td> <td>50 V</td> <td>3936</td>	3-Phase PWM Current-Controlled DMOS Driver	±3.0 A	50 V	3936
Dual Full Bridge with Protection & Diagnostics±500 mA30 V3976PWM Current-Controlled Dual Full Bridge±650 mA30 V3966PWM Current-Controlled Dual Full Bridge±650 mA30 V3967PWM Current-Controlled Dual Full Bridge±750 mA45 V2916PWM Current-Controlled Dual Full Bridge±750 mA45 V2919PWM Current-Controlled Dual Full Bridge±750 mA45 V2919PWM Current-Controlled Dual Full Bridge±750 mA45 V2919PWM Current-Controlled Dual Full Bridge±750 mA45 V6219PWM Current-Controlled Dual Full Bridge±1.0 A35 V3973PWM Current-Controlled Dual Full Bridge±1.3 A50 V3953PWM Current-Controlled Dual DMOS Full Bridge±1.5 A50 V3955PWM Current-Controlled DMOS Full Bridge±1.5 A50 V3955PWM Current-Controlled Microstepping Full Bridge±1.5 A50 V3957PWM Current-Controlled Dual DMOS Full Bridge±1.5 A50 V3972PWM Current-Controlled Dual DMOS Full Bridge±1.5 A50 V3957PWM Current-Controlled Dual DMOS Full Bridge±2.0 A50 V3952PWM Current-Controlled Dual DMOS Full Bridge±2.0 A50 V3958Microstepping Translator/Dai DMOS Full Bridge±2.5 A35 V3977PWM Current-Controlled DMOS Full Bridge±2.0 A50 V3958Microstepping Translator/Driver1.0 A46 V7050Unipolar Stepper-Motor T	INTEGRATED BRIDGE DRIVERS	FOR DC AND B	SIPOLAR STEP	PER MOTORS
PWM Current-Controlled Dual Full Bridge±650 mA30 V3966PWM Current-Controlled Dual Full Bridge±650 mA30 V3968Microstepping Translator/Dual Full Bridge±750 mA45 V2916PWM Current-Controlled Dual Full Bridge±750 mA45 V2919PWM Current-Controlled Dual Full Bridge±750 mA45 V2919PWM Current-Controlled Dual Full Bridge±750 mA45 V6219PWM Current-Controlled Dual Full Bridge±800 mA33 V3964PWM Current-Controlled Dual Full Bridge±1.0 A35 V3973PWM Current-Controlled Dual Full Bridge±1.5 A45 V2917PWM Current-Controlled Dual Full Bridge±1.5 A50 V3948PWM Current-Controlled Dual Full Bridge±1.5 A50 V3948PWM Current-Controlled Dual Full Bridge±1.5 A50 V3955PWM Current-Controlled Microstepping Full Bridge±1.5 A50 V3957PWM Current-Controlled Dual DMOS Full Bridge±1.5 A50 V3972PWM Current-Controlled Dual DMOS Full Bridge±2.0 A50 V3952PWM Current-Controlled Dual DMOS Full Bridge±2.0 A50 V3958Microstepping Translator/Dual DMOS Full Bridge±2.0 A50 V3957PWM Current-Controlled DMOS Full Bridge±2.0 A50 V3958Microstepper-Motor Translator/Driver1.0 A46 V7050Unipolar Stepper-Motor Translator/Driver1.5 A46 V7024 & 7029Unipolar Stepper-Motor Quad	PWM Current-Controlled Dual Full Bridge	±500 mA	18 V	3965
PWM Current-Controlled Dual Full Bridge±650 mA30 V3968Microstepping Translator/Dual Full Bridge±750 mA30 V3967PWM Current-Controlled Dual Full Bridge±750 mA45 V2916PWM Current-Controlled Dual Full Bridge±750 mA45 V6219PWM Current-Controlled Dual Full Bridge±750 mA45 V6219PWM Current-Controlled Dual Full Bridge±800 mA33 V3964PWM Current-Controlled Dual Full Bridge±1.0 A35 V3973PWM Current-Controlled Dual Full Bridge±1.3 A50 V3953PWM Current-Controlled Dual Full Bridge±1.5 A45 V2917PWM Current-Controlled Dual Full Bridge±1.5 A50 V3953PWM Current-Controlled DMOS Full Bridge±1.5 A50 V3955PWM Current-Controlled Microstepping Full Bridge±1.5 A50 V3957PWM Current-Controlled Microstepping Full Bridge±1.5 A50 V3974PWM Current-Controlled Dual DMOS Full Bridge±1.5 A50 V3974PWM Current-Controlled Dual DMOS Full Bridge±2.0 A50 V3952PWM Current-Controlled DMOS Full Bridge±2.0 A50 V3959Microstepping Translator/Dual DMOS Full Bridge±2.5 A35 V3977PWM Current-Controlled DMOS Full Bridge±2.5 A50 V3959UniPOLAR STEPPER MOTOR & OTHER STOR & OTHERSUnipolar Stepper-Motor Translator/Driver1.0 A46 V7024Unipolar Stepper-Motor Quad Drivers1.5 A46 V7	Dual Full Bridge with Protection & Diagnostics	±500 mA	30 V	3976
Microstepping Translator/Dual Full Bridge±750 mA30 V3967PWM Current-Controlled Dual Full Bridge±750 mA45 V2916PWM Current-Controlled Dual Full Bridge±750 mA45 V2919PWM Current-Controlled Dual Full Bridge±750 mA45 V6219PWM Current-Controlled Dual Full Bridge±800 mA33 V3964PWM Current-Controlled Dual IB Bridge±1.0 A35 V3973PWM Current-Controlled Dual Full Bridge±1.3 A50 V3953PWM Current-Controlled Dual Full Bridge±1.5 A45 V2917PWM Current-Controlled Dual Full Bridge±1.5 A50 V3955PWM Current-Controlled DMOS Full Bridge±1.5 A50 V3957PWM Current-Controlled Microstepping Full Bridge±1.5 A50 V3957PWM Current-Controlled Dual DMOS Full Bridge±1.5 A50 V3972PWM Current-Controlled Dual DMOS Full Bridge±1.5 A50 V3974PWM Current-Controlled Dual DMOS Full Bridge±2.0 A50 V3958Microstepping Translator/Dual DMOS Full Bridge±2.0 A50 V3959UNIPOLAR STEPPER MOTOR & OTHER DRIVERSUnipolar Stepper-Motor Translator/Driver1.0 A46 V7050Unipolar Stepper-Motor Translator/Driver1.5 A50 V5804Unipolar Stepper-Motor Quad DriverUnipolar Stepper-Motor Quad Driver1.8 A50 V2540Unipolar Stepper-Motor Translator/Driver1.0 A46 V7051Unipolar Stepper-Motor Quad Driver2.0 A	PWM Current-Controlled Dual Full Bridge	±650 mA	30 V	3966
PWM Current-Controlled Dual Full Bridge±750 mA45 V2916PWM Current-Controlled Dual Full Bridge±750 mA45 V2919PWM Current-Controlled Dual Full Bridge±750 mA45 V6219PWM Current-Controlled Dual Full Bridge±800 mA33 V3964PWM Current-Controlled Dual Full Bridge±1.0 A35 V3973PWM Current-Controlled Full Bridge±1.3 A50 V3953PWM Current-Controlled Dual Full Bridge±1.5 A45 V2917PWM Current-Controlled Dual Full Bridge±1.5 A50 V3948PWM Current-Controlled Microstepping Full Bridge±1.5 A50 V3955PWM Current-Controlled Microstepping Full Bridge±1.5 A50 V3957PWM Current-Controlled Dual DMOS Full Bridge±1.5 A50 V3972PWM Current-Controlled Dual DMOS Full Bridge±1.5 A50 V3974PWM Current-Controlled Dual DMOS Full Bridge±2.0 A50 V3952PWM Current-Controlled DMOS Full Bridge±2.0 A50 V3958Microstepping Translator/Dual DMOS Full Bridge±3.0 A50 V3959UNIPOLAR STEPPER MOTOR & OTHER DRIVERSUnipolar Stepper-Motor Translator/Driver1.0 A46 V7050Unipolar Stepper-Motor Quad Drivers1.5 A50 V2540Unipolar Stepper-Motor Quad Driver1.8 A50 V2540Unipolar Stepper-Motor Quad Driver2.0 A46 V7051Unipolar Stepper-Motor Quad Driver2.0 A46 V7051 <td>PWM Current-Controlled Dual Full Bridge</td> <td>±650 mA</td> <td>30 V</td> <td>3968</td>	PWM Current-Controlled Dual Full Bridge	±650 mA	30 V	3968
PWM Current-Controlled Dual Full Bridge±750 mA45 V2919PWM Current-Controlled Dual Full Bridge±750 mA45 V6219PWM Current-Controlled Dual Full Bridge±800 mA33 V3964PWM Current-Controlled Dual DMOS Full Bridge±1.0 A35 V3973PWM Current-Controlled Dual Full Bridge±1.3 A50 V3953PWM Current-Controlled Dual Stell Bridge±1.5 A45 V2917PWM Current-Controlled DMOS Full Bridge±1.5 A50 V3948PWM Current-Controlled Microstepping Full Bridge±1.5 A50 V3955PWM Current-Controlled Microstepping Full Bridge±1.5 A50 V3957PWM Current-Controlled Dual DMOS Full Bridge±1.5 A50 V3972PWM Current-Controlled Dual DMOS Full Bridge±1.5 A50 V3972PWM Current-Controlled Dual DMOS Full Bridge±2.0 A50 V3952PWM Current-Controlled Dual DMOS Full Bridge±2.0 A50 V3958Microstepping Translator/Dual DMOS Full Bridge±2.5 A35 V3977PWM Current-Controlled DMOS Full Bridge±3.0 A50 V3959Unipolar Stepper-Motor Translator/Driver1.0 A46 V7050Unipolar Stepper-Motor Quad Driver1.5 A46 V7042Unipolar Stepper-Motor Quad Driver2.0 A46 V7026Unipolar Stepper-Motor Quad Driver3.0 A46 V7026Unipolar Stepper-Motor Quad Driver3.0 A46 V7026	Microstepping Translator/Dual Full Bridge	±750 mA	30 V	3967
PWM Current-Controlled Dual Full Bridge±750 mA45 V6219PWM Current-Controlled Dual Full Bridge±800 mA33 V3964PWM Current-Controlled Dual DMOS Full Bridge±1.0 A35 V3973PWM Current-Controlled Dual Full Bridge±1.3 A50 V3953PWM Current-Controlled DMOS Full Bridge±1.5 A45 V2917PWM Current-Controlled DMOS Full Bridge±1.5 A50 V3948PWM Current-Controlled Microstepping Full Bridge±1.5 A50 V3955PWM Current-Controlled Microstepping Full Bridge±1.5 A50 V3957PWM Current-Controlled DMOS Full Bridge±1.5 A50 V3974PWM Current-Controlled Dual DMOS Full Bridge±1.5 A50 V3972PWM Current-Controlled Dual DMOS Full Bridge±2.0 A50 V3952PWM Current-Controlled DMOS Full Bridge±2.0 A50 V3958Microstepping Translator/Dual DMOS Full Bridge±2.0 A50 V3959VMPOLAR STEPPER MOTOR & OTHER DRIVERSUNIPOLAR STEPPER MOTOR & OTHER DRIVERS1.0 A46 VUnipolar Stepper-Motor Translator/Driver1.0 A46 V7050Unipolar Stepper-Motor Quad Driver1.5 A46 V7042Unipolar Stepper-Motor Quad Driver1.5 A46 V7042Unipolar Stepper-Motor Quad Driver2.0 A46 V7042Unipolar Stepper-Motor Quad Driver1.5 A46 V7021Unipolar Stepper-Motor Quad Driver2.0 A46 V7051Unipolar Stepper-Motor Quad	PWM Current-Controlled Dual Full Bridge	±750 mA	45 V	2916
PWM Current-Controlled Dual Full Bridge±800 mA33 V3964PWM Current-Controlled Dual DMOS Full Bridge±1.0 A35 V3973PWM Current-Controlled Full Bridge±1.3 A50 V3953PWM Current-Controlled Dual Full Bridge±1.5 A45 V2917PWM Current-Controlled DMOS Full Bridge±1.5 A50 V3948PWM Current-Controlled Microstepping Full Bridge±1.5 A50 V3955PWM Current-Controlled Microstepping Full Bridge±1.5 A50 V3957PWM Current-Controlled DMOS Full Bridge±1.5 A50 V3972PWM Current-Controlled Dual DMOS Full Bridge±1.5 A50 V3972PWM Current-Controlled Dual DMOS Full Bridge±1.5 A50 V3972PWM Current-Controlled Dual DMOS Full Bridge±2.0 A50 V3952PWM Current-Controlled DMOS Full Bridge±2.0 A50 V3958Microstepping Translator/Dual DMOS Full Bridge±2.0 A50 V3959UNIPOLAR STEPPER MOTOR & OTHER DRIVERSUnipolar Stepper-Motor Translator/Driver1.0 A46 V7050Unipolar Stepper-Motor Quad Driver1.5 A46 V7042Unipolar Stepper-Motor Quad Driver1.5 A46 V7042Unipolar Stepper-Motor Quad Driver1.8 A50 V2540Unipolar Stepper-Motor Quad Driver2.0 A46 V7051Unipolar Stepper-Motor Quad Driver3.0 A46 V7026Unipolar Stepper-Motor Quad Driver3.0 A46 V7026 <td>PWM Current-Controlled Dual Full Bridge</td> <td>±750 mA</td> <td>45 V</td> <td>2919</td>	PWM Current-Controlled Dual Full Bridge	±750 mA	45 V	2919
PWM Current-Controlled Dual DMOS Full Bridge±1.0 A35 V3973PWM Current-Controlled Full Bridge±1.3 A50 V3953PWM Current-Controlled Dual Full Bridge±1.5 A45 V2917PWM Current-Controlled DMOS Full Bridge±1.5 A50 V3948PWM Current-Controlled Microstepping Full Bridge±1.5 A50 V3955PWM Current-Controlled Microstepping Full Bridge±1.5 A50 V3957PWM Current-Controlled Dual DMOS Full Bridge±1.5 A50 V3972PWM Current-Controlled Dual DMOS Full Bridge±1.5 A50 V3974PWM Current-Controlled Dual DMOS Full Bridge±2.0 A50 V3952PWM Current-Controlled Full Bridge±2.0 A50 V3952PWM Current-Controlled DMOS Full Bridge±2.0 A50 V3958Microstepping Translator/Dual DMOS Full Bridge±2.0 A50 V3959PWM Current-Controlled DMOS Full Bridge±2.0 A50 V3959Microstepping Translator/Dual DMOS Full Bridge±2.0 A50 V3959Unipolar Stepper-Motor Translator/Driver1.0 A46 V7050Unipolar Stepper-Motor Translator/Driver1.5 A46 V7042Unipolar Stepper-Motor Quad Driver1.5 A46 V7042Unipolar Stepper-Motor Quad Driver1.8 A50 V2540Unipolar Stepper-Motor Quad Driver2.0 A46 V7051Unipolar Stepper-Motor Quad Driver3.0 A46 V7026Unipolar Stepper-Motor Quad Driver3.0 A <td>PWM Current-Controlled Dual Full Bridge</td> <td>±750 mA</td> <td>45 V</td> <td>6219</td>	PWM Current-Controlled Dual Full Bridge	±750 mA	45 V	6219
PWM Current-Controlled Full Bridge±1.3 A50 V3953PWM Current-Controlled Dual Full Bridge±1.5 A45 V2917PWM Current-Controlled DMOS Full Bridge±1.5 A50 V3948PWM Current-Controlled Microstepping Full Bridge±1.5 A50 V3955PWM Current-Controlled Microstepping Full Bridge±1.5 A50 V3957PWM Current-Controlled Dual DMOS Full Bridge±1.5 A50 V3972PWM Current-Controlled Dual DMOS Full Bridge±1.5 A50 V3974PWM Current-Controlled Dual DMOS Full Bridge±2.0 A50 V3952PWM Current-Controlled DMOS Full Bridge±2.0 A50 V3952PWM Current-Controlled DMOS Full Bridge±2.0 A50 V3958Microstepping Translator/Dual DMOS Full Bridge±2.0 A50 V3959PWM Current-Controlled DMOS Full Bridge±3.0 A50 V3959PWM Current-Controlled DMOS Full Bridge±3.0 A50 V3959PWM Current-Controlled DMOS Full Bridge±3.0 A50 V3959Unipolar Stepper-Motor Translator/Driver1.0 A46 V7050Unipolar Stepper-Motor Quad Drivers1.5 A46 V7042Unipolar Stepper-Motor Quad Driver1.8 A50 V2540Unipolar Stepper-Motor Quad Driver2.0 A46 V7026Unipolar Stepper-Motor Quad Driver3.0 A46 V7026Unipolar Stepper-Motor Quad Driver3.0 A46 V7044	PWM Current-Controlled Dual Full Bridge	±800 mA	33 V	3964
PWM Current-Controlled Dual Full Bridge±1.5 A45 V2917PWM Current-Controlled DMOS Full Bridge±1.5 A50 V3948PWM Current-Controlled Microstepping Full Bridge±1.5 A50 V3955PWM Current-Controlled Microstepping Full Bridge±1.5 A50 V3957PWM Current-Controlled Dual DMOS Full Bridge±1.5 A50 V3972PWM Current-Controlled Dual DMOS Full Bridge±1.5 A50 V3974PWM Current-Controlled Dual DMOS Full Bridge±2.0 A50 V3952PWM Current-Controlled DMOS Full Bridge±2.0 A50 V3958Microstepping Translator/Dual DMOS Full Bridge±2.5 A35 V3977PWM Current-Controlled DMOS Full Bridge±3.0 A50 V3959Unipolar Stepper-Motor Translator/Driver1.0 A46 V7050Unipolar Stepper-Motor Translator/Driver1.5 A46 V7024 & 7029Unipolar Stepper-Motor Quad Drivers1.5 A46 V7042Unipolar Stepper-Motor Quad Driver1.8 A50 V2540Unipolar Stepper-Motor Quad Driver2.0 A46 V7051Unipolar Stepper-Motor Quad Driver3.0 A46 V7026Unipolar Stepper-Motor Quad Driver3.0 A46 V7026	PWM Current-Controlled Dual DMOS Full Bridge	±1.0 A	35 V	3973
PWM Current-Controlled DMOS Full Bridge±1.5 A50 V3948PWM Current-Controlled Microstepping Full Bridge±1.5 A50 V3955PWM Current-Controlled Microstepping Full Bridge±1.5 A50 V3957PWM Current-Controlled Dual DMOS Full Bridge±1.5 A50 V3972PWM Current-Controlled Dual DMOS Full Bridge±1.5 A50 V3974PWM Current-Controlled Dual DMOS Full Bridge±2.0 A50 V3952PWM Current-Controlled Full Bridge±2.0 A50 V3958Microstepping Translator/Dual DMOS Full Bridge±2.5 A35 V3977PWM Current-Controlled DMOS Full Bridge±3.0 A50 V3959Microstepping Translator/Dual DMOS Full Bridge±3.0 A50 V3959UNIPOLAR STEPPER MOTOR & OTHER DRIVERSUnipolar Stepper-Motor Translator/Driver1.0 A46 V7050Unipolar Stepper-Motor Translator/Driver1.5 A46 V7024 & 7029Unipolar Stepper-Motor Quad Driver1.5 A46 V7042Unipolar Stepper-Motor Quad Driver1.8 A50 V2540Unipolar Stepper-Motor Quad Driver2.0 A46 V7051Unipolar Stepper-Motor Quad Driver3.0 A46 V7026Unipolar Stepper-Motor Quad Driver3.0 A46 V7026Unipolar Stepper-Motor Quad Driver3.0 A46 V7026	PWM Current-Controlled Full Bridge	±1.3 A	50 V	3953
PWM Current-Controlled Microstepping Full Bridge±1.5 A50 V3955PWM Current-Controlled Microstepping Full Bridge±1.5 A50 V3957PWM Current-Controlled Dual DMOS Full Bridge±1.5 A50 V3972PWM Current-Controlled Dual DMOS Full Bridge±1.5 A50 V3974PWM Current-Controlled Full Bridge±2.0 A50 V3952PWM Current-Controlled DMOS Full Bridge±2.0 A50 V3958Microstepping Translator/Dual DMOS Full Bridge±2.5 A35 V3977PWM Current-Controlled DMOS Full Bridge±3.0 A50 V3959UNIPOLAR STEPPER WOTOR & OTHER BRIVERSUnipolar Stepper-Motor Translator/Driver1.0 A46 V7050Unipolar Stepper-Motor Translator/Driver1.5 A46 V7042Unipolar Stepper-Motor Quad Drivers1.5 A46 V7042Unipolar Stepper-Motor Quad Driver1.8 A50 V2540Unipolar Stepper-Motor Quad Driver3.0 A46 V7051Unipolar Stepper-Motor Quad Driver3.0 A46 V7024	PWM Current-Controlled Dual Full Bridge	±1.5 A	45 V	2917
PWM Current-Controlled Microstepping Full Bridge±1.5 A50 V3957PWM Current-Controlled Dual DMOS Full Bridge±1.5 A50 V3972PWM Current-Controlled Dual DMOS Full Bridge±1.5 A50 V3974PWM Current-Controlled Full Bridge±2.0 A50 V3952PWM Current-Controlled DMOS Full Bridge±2.0 A50 V3958Microstepping Translator/Dual DMOS Full Bridge±2.0 A50 V3959UNIPOLAR STEPPER MOTOR & OTHER DRIVERSUnipolar Stepper-Motor Translator/Driver1.0 A46 V7050Unipolar Stepper-Motor Translator/Driver1.5 A46 V7024 & 7029Unipolar Stepper-Motor Quad Drivers1.5 A46 V7042Unipolar Stepper-Motor Translator/Driver1.6 A46 V7042Unipolar Stepper-Motor Quad Driver1.6 A46 V7024Unipolar Stepper-Motor Quad Driver1.6 A46 V7042Unipolar Stepper-Motor Quad Driver1.8 A50 V2540Unipolar Stepper-Motor Translator/Driver2.0 A46 V7051Unipolar Stepper-Motor Quad Driver3.0 A46 V7024	PWM Current-Controlled DMOS Full Bridge	±1.5 A	50 V	3948
PWM Current-Controlled Dual DMOS Full Bridge±1.5 A50 V3972PWM Current-Controlled Dual DMOS Full Bridge±1.5 A50 V3974PWM Current-Controlled Full Bridge±2.0 A50 V3952PWM Current-Controlled DMOS Full Bridge±2.0 A50 V3958Microstepping Translator/Dual DMOS Full Bridge±2.5 A35 V3977PWM Current-Controlled DMOS Full Bridge±3.0 A50 V3959UNIPOLAR STEPPER MOTOR & OTHER DRIVERSUnipolar Stepper-Motor Translator/Driver1.0 A46 V7050Unipolar Stepper-Motor Translator/Driver1.5 A46 V7024 & 7029Unipolar Stepper-Motor Quad Drivers1.5 A46 V7042Unipolar Stepper-Motor Quad Driver1.8 A50 V2540Unipolar Stepper-Motor Quad Driver2.0 A46 V7051Unipolar Stepper-Motor Quad Driver3.0 A46 V7026Unipolar Stepper-Motor Quad Driver3.0 A46 V7026	PWM Current-Controlled Microstepping Full Bridge	±1.5 A	50 V	3955
PWM Current-Controlled Dual DMOS Full Bridge±1.5 A50 V3974PWM Current-Controlled Full Bridge±2.0 A50 V3952PWM Current-Controlled DMOS Full Bridge±2.0 A50 V3958Microstepping Translator/Dual DMOS Full Bridge±2.5 A35 V3977PWM Current-Controlled DMOS Full Bridge±3.0 A50 V3959UNIPOLAR STEPPER MOTOR & OTHER DRIVERSUnipolar Stepper-Motor Translator/Driver1.0 A46 V7050Unipolar Stepper-Motor Translator/Driver1.25 A50 V5804Unipolar Stepper-Motor Quad Drivers1.5 A46 V7024 & 7029Unipolar Stepper-Motor Quad Driver1.8 A50 V2540Unipolar Stepper-Motor Translator/Driver2.0 A46 V7051Unipolar Stepper-Motor Quad Driver3.0 A46 V7024Unipolar Stepper-Motor Quad Driver3.0 A46 V7024Unipolar Stepper-Motor Quad Driver3.0 A46 V7024	PWM Current-Controlled Microstepping Full Bridge	±1.5 A	50 V	3957
PWM Current-Controlled Full Bridge±2.0 A50 V3952PWM Current-Controlled DMOS Full Bridge±2.0 A50 V3958Microstepping Translator/Dual DMOS Full Bridge±2.5 A35 V3977PWM Current-Controlled DMOS Full Bridge±3.0 A50 V3959UNIPOLAR STEPPER MOTOR & OTHER DRIVERSUnipolar Stepper-Motor Translator/Driver1.0 A46 V7050Unipolar Stepper-Motor Translator/Driver1.25 A50 V5804Unipolar Stepper-Motor Quad Drivers1.5 A46 V7024 & 7029Unipolar Stepper-Motor Quad Driver1.8 A50 V2540Unipolar Stepper-Motor Translator/Driver2.0 A46 V7051Unipolar Stepper-Motor Quad Driver3.0 A46 V7026Unipolar Stepper-Motor Quad Driver3.0 A46 V7026	PWM Current-Controlled Dual DMOS Full Bridge	±1.5 A	50 V	3972
PWM Current-Controlled DMOS Full Bridge±2.0 A50 V3958Microstepping Translator/Dual DMOS Full Bridge±2.5 A35 V3977PWM Current-Controlled DMOS Full Bridge±3.0 A50 V3959UNIPOLAR STEPPER MOTOR & OTHER DRIVERSUnipolar Stepper-Motor Translator/Driver1.0 A46 V7050Unipolar Stepper-Motor Translator/Driver1.25 A50 V5804Unipolar Stepper-Motor Quad Drivers1.5 A46 V7024 & 7029Unipolar Stepper-Motor Quad Driver1.8 A50 V2540Unipolar Stepper-Motor Translator/Driver2.0 A46 V7051Unipolar Stepper-Motor Quad Driver3.0 A46 V7024	PWM Current-Controlled Dual DMOS Full Bridge	±1.5 A	50 V	3974
Microstepping Translator/Dual DMOS Full Bridge±2.5 A35 V3977PWM Current-Controlled DMOS Full Bridge±3.0 A50 V3959UNIPOLAR STEPPER MOTOR & OTHER DRIVERSUnipolar Stepper-Motor Translator/Driver1.0 A46 V7050Unipolar Stepper-Motor Translator/Driver1.25 A50 V5804Unipolar Stepper-Motor Quad Drivers1.5 A46 V7024 & 7029Unipolar Stepper-Motor Quad Driver1.5 A46 V7042Unipolar Stepper-Motor Quad Driver1.8 A50 V2540Unipolar Stepper-Motor Translator/Driver2.0 A46 V7051Unipolar Stepper-Motor Quad Driver3.0 A46 V7024	PWM Current-Controlled Full Bridge	±2.0 A	50 V	3952
PWM Current-Controlled DMOS Full Bridge±3.0 A50 V3959UNIPOLAR STEPPER MOTOR & OTHER DRIVERSUnipolar Stepper-Motor Translator/Driver1.0 A46 V7050Unipolar Stepper-Motor Translator/Driver1.25 A50 V5804Unipolar Stepper-Motor Quad Drivers1.5 A46 V7024 & 7029Unipolar Stepper-Motor Quad Driver1.8 A50 V2540Unipolar Stepper-Motor Quad Driver1.8 A50 V2540Unipolar Stepper-Motor Quad Driver3.0 A46 V7026Unipolar Stepper-Motor Quad Driver3.0 A46 V7024	PWM Current-Controlled DMOS Full Bridge	±2.0 A	50 V	3958
UNIPOLAR STEPPER MOTOR & OTHER DRIVERSUnipolar Stepper-Motor Translator/Driver1.0 A46 V7050Unipolar Stepper-Motor Translator/Driver1.25 A50 V5804Unipolar Stepper-Motor Quad Drivers1.5 A46 V7024 & 7029Unipolar Microstepper-Motor Quad Driver1.5 A46 V7042Unipolar Stepper-Motor Quad Driver1.8 A50 V2540Unipolar Stepper-Motor Translator/Driver2.0 A46 V7051Unipolar Stepper-Motor Quad Driver3.0 A46 V7026Unipolar Microstepper-Motor Quad Driver3.0 A46 V7044	Microstepping Translator/Dual DMOS Full Bridge	±2.5 A	35 V	3977
Unipolar Stepper-Motor Translator/Driver1.0 A46 V7050Unipolar Stepper-Motor Translator/Driver1.25 A50 V5804Unipolar Stepper-Motor Quad Drivers1.5 A46 V7024 & 7029Unipolar Microstepper-Motor Quad Driver1.5 A46 V7042Unipolar Stepper-Motor Quad Driver1.8 A50 V2540Unipolar Stepper-Motor Translator/Driver2.0 A46 V7051Unipolar Stepper-Motor Quad Driver3.0 A46 V7026	PWM Current-Controlled DMOS Full Bridge	±3.0 A	50 V	3959
Unipolar Stepper-Motor Translator/Driver1.25 A50 V5804Unipolar Stepper-Motor Quad Drivers1.5 A46 V7024 & 7029Unipolar Microstepper-Motor Quad Driver1.5 A46 V7042Unipolar Stepper-Motor Quad Driver1.8 A50 V2540Unipolar Stepper-Motor Translator/Driver2.0 A46 V7051Unipolar Stepper-Motor Quad Driver3.0 A46 V7026	UNIPOLAR STEPPE	R MOTOR & OT	THER DRIVERS	8
Unipolar Stepper-Motor Quad Drivers1.5 A46 V7024 & 7029Unipolar Microstepper-Motor Quad Driver1.5 A46 V7042Unipolar Stepper-Motor Quad Driver1.8 A50 V2540Unipolar Stepper-Motor Translator/Driver2.0 A46 V7051Unipolar Stepper-Motor Quad Driver3.0 A46 V7026Unipolar Microstepper-Motor Quad Driver3.0 A46 V7044	Unipolar Stepper-Motor Translator/Driver	1.0 A	46 V	7050
Unipolar Microstepper-Motor Quad Driver1.5 A46 V7042Unipolar Stepper-Motor Quad Driver1.8 A50 V2540Unipolar Stepper-Motor Translator/Driver2.0 A46 V7051Unipolar Stepper-Motor Quad Driver3.0 A46 V7026Unipolar Microstepper-Motor Quad Driver3.0 A46 V7044	Unipolar Stepper-Motor Translator/Driver	1.25 A	50 V	5804
Unipolar Stepper-Motor Quad Driver1.8 A50 V2540Unipolar Stepper-Motor Translator/Driver2.0 A46 V7051Unipolar Stepper-Motor Quad Driver3.0 A46 V7026Unipolar Microstepper-Motor Quad Driver3.0 A46 V7044	Unipolar Stepper-Motor Quad Drivers	1.5 A	46 V	7024 & 7029
Unipolar Stepper-Motor Translator/Driver2.0 A46 V7051Unipolar Stepper-Motor Quad Driver3.0 A46 V7026Unipolar Microstepper-Motor Quad Driver3.0 A46 V7044	Unipolar Microstepper-Motor Quad Driver	1.5 A	46 V	7042
Unipolar Stepper-Motor Quad Driver3.0 A46 V7026Unipolar Microstepper-Motor Quad Driver3.0 A46 V7044	Unipolar Stepper-Motor Quad Driver	1.8 A	50 V	2540
Unipolar Stepper-Motor Quad Driver3.0 A46 V7026Unipolar Microstepper-Motor Quad Driver3.0 A46 V7044	Unipolar Stepper-Motor Translator/Driver	2.0 A	46 V	7051
	Unipolar Stepper-Motor Quad Driver	3.0 A	46 V	7026
Unipolar Stepper-Motor Translator/Driver 3.0 A 46 V 7052	Unipolar Microstepper-Motor Quad Driver	3.0 A	46 V	7044
	Unipolar Stepper-Motor Translator/Driver	3.0 A	46 V	7052

* Current is maximum specified test condition, voltage is maximum rating. See specification for sustaining voltage limits or over-current protection voltage limits. Negative current is defined as coming out of (sourcing) the output.

† Complete part number includes additional characters to indicate operating temperature range and package style.

Also, see 3175, 3177, 3235, and 3275 Hall-effect sensors for use with brushless dc motors.



115 Northeast Cutoff, Box 15036 Worcester, Massachusetts 01615-0036 (508) 853-5000