
## MC4062P\*

## **Advance Information**




This integrated circuit offers the designer additional versatility in logic design. When any two or all three of the inputs are raised to the "1" level, the output goes to the "1" level. The output, Z, and its complement,  $\overline{Z}$ , are both available.

INPUT			OUTPUT	
Α	В	С	Z	Z
0	0	0	0	1
0	0	1	0	1
0	1	0	0	. 1
0	1	1	1	0
1	0	0	0	1
1	0	1	1	0
1	1	0	1	0
1	1	1	1 1	0

Total Power Dissipation = 75 mW typ/pkg Propagation Delay Time = 20 ns typ (Z Output) 11 ns typ (Z Output)

## CIRCUIT SCHEMATIC (1/2 OF DEVICE SHOWN)



This is advance information on a new introduction and specifications are subject to change without notice.

\*P suffix = TO-116 dual in-line plastic package (Case 605).