





T.			$U_f$	$I_f$	$U_a$	$U_g$	$I_a$	$S$	$\mu$	$R_i$	$R_k$
			V	A	V	V	mA	mA/V	V/V	k $\Omega$	$\Omega$
<b>2 AF 4-A<sup>1)</sup></b>	amer	1	2,35	0,6	80	-2,4	16	6,6	15	2,27	150
<b>3 AF 4-A<sup>1)</sup></b>	amer	1	3,2	0,45	100	-2,6	20	7,5	16	2,13	150
<b>2 BN 4<sup>2)</sup></b>	amer	2	2,3	0,6	150	-2	9	6,8	43	6,3	220
<b>3 BN 4<sup>2)</sup></b>	amer	2	2,8	0,45							
<b>2 T 4<sup>1)</sup></b>	amer	1	2,35	0,6	80		13	7	13	1,86	150

<sup>1)</sup> vide gr. 131

<sup>2)</sup> vide gr. 127



**2AF4**



**2BN4**