



T.			U_f	I_f	U_a	U_{g2}	U_{g3}	U_{g1}	I_o	I_{g2}	I_{g1}	S
			V	A	V	V	V	V	V	mA	mA	mA
AL 860 RL 4,2 P 6 4 II 1 JI	RFT	5	2,4/4,8	0,56/0,28	$\left. \begin{array}{l} 150^1) \\ 240^2) \\ 200^3) \\ 250 \end{array} \right\}$	150	0	-7	35	6,5		6
	TIF	1	2,1/4,2	0,65/0,325		160	0	-10,2	31	4		6
	CCCP	2	2,1/4,2 (1,95 ÷ 2,35) (3,9 ÷ 4,7)	0,65/0,325		150	15	-20		10	1	
maximum ($I_k = 50$ mA; $P_a = 7,5$ W; $P_{g2} = 1,5$ W)												
4 II 1	CCCP	3	4	1	240 ⁴⁾	140	0	-11	22	6		2,1
5 A 6	int	4	2,5/5 (±15%)	0,46/0,23	$\left. \begin{array}{l} 150^5) \\ 150^6) \\ 150^7) \end{array} \right\}$	150	0	-15	40	7	1	
						150	0	-24	40	11	1,2	
						150	0	-75	40		3	

- ¹⁾ Cl. A1; $R_o = 6$ k Ω ; $P_o = 1,5$ W
²⁾ Cl. A1; $R_o = 7$ k Ω ; $P_o = 2,6$ W
³⁾ Cl. C; $f = 30$ MHz; $U_{g1} \approx 18$ V; $P_o = 4,2$ W
⁴⁾ Cl. A1; $R_o = 20$ k Ω ; $P_o = 1$ W
⁵⁾ Cl. B; $U_a = U_b$; $R_{g2} = 1500$ Ω ; $U_{g1} \approx 23$ V; $R_{g1} = 15$ k Ω ;
 $f = 70$ MHz; $P_o = 2,8$ W
⁶⁾ Cl. C; $U_{g1} \approx 35$ V; $R_{g1} = 20$ k Ω ; $f = 70$ MHz; $P_o = 3,1$ W
⁷⁾ maximum ($P_a = 5$ W; $P_{g2} = 2$ W)

T.	$C_{g1/k}$ pF	$C_{o,k}$ pF	$C_{g1/a}$ pF	vide
AL 860	10	11	0,09	
4 II 1 JI	8,5	9,4	0,1	
5 A 6	8,5	9,5	0,1	*6
	8,5	6	0,15	*5

Equivalents

CO-122	CCCP = 4 П 1
4 L 20	Tes = 4 П 1 Л

