

Trioda

6C4

RCA


Wzmacniacz kl. A, wzmacniacz mocy
w.cz. i oscylator kl. C (telegrafia)

Miniaturowy



$$U_z = 6,3 \text{ V}$$

$$I_z = 0,15 \text{ A}$$



Wartości robocze

	Wzmac. kl. A przy 50 MHz		
	100	250	300
U_a	100	250	300
U_s	0	-8,5	-27
I_a	11,5	10,5	25
I_s	—	—	7
K_a	19,5	17	—
S_a	3,1	2,2	—
ρ_a	6,25	7,7	—
P_{wzb}	—	—	0,35
$P_{a\sim}$	—	—	5,5

Wartości maksymalne

	kl. A		kl.C
	300	300	
U_{amax}	300	300	V
U_{smax}	—	-50	V
I_{amax}	—	25	mA
I_{smax}	—	8	mA
P_{amax}	3,5	5	W
$U_{wl\ kszcz}$	200		V

Pojemności

C_{wej}	1,8	pF
C_{wyj}	1,3	pF
$C_{s/a}$	1,6	pF

TYPY PODOBNE

EC 90

