


Pentoda mocy

DL 72

Philips


Wzmacniacz mocy m. cz.¹⁾

Subminiaturowy



$$U_z = 1,25 \text{ V}$$

$$I_z = 0,025 \text{ A}$$



Wartości robocze

| | | |
|--------------|-------|------------|
| U_a | 45 | V |
| U_{S2} | 45 | V |
| U_{S1} | -4,5 | V |
| $U_{S1\sim}$ | 3 | V |
| I_a | 1,25 | mA |
| I_{S2} | 0,4 | mA |
| S_a | 0,5 | mA/V |
| ρ_a | 225 | k Ω |
| R_a | 30 | k Ω |
| R_{S1} | 10 | M Ω |
| $P_{a\sim}$ | 0,023 | W |
| h | 10 | % |
| $K_{S2/S1}$ | 5 | V/V |

Wartości maksymalne

| | | |
|-------------|------|------------|
| U_{amax} | 45 | V |
| U_{S2max} | 45 | V |
| I_{kmax} | 2 | mA |
| P_{amax} | 0,06 | W |
| P_{S2max} | 0,02 | W |
| R_{S1max} | 10 | M Ω |

¹⁾ do aparatów słuchowych

TYPY PODOBNE

DL 67, DL 68, DL 71

