

# PCF806

## Triode Frame Grid Pentode VHF Frequency Changer 0.3A, 8V Heater

	Triode	Pentode	
<b>Rating</b>			
$P_{a(max)}$	1.5	2	W
<b>Characteristics</b>			
$V_a$	100	170	V
$V_{g_2}$	...	150	V
$V_{g_1}$	-3	-1.2	V
$I_a$	14	10	mA
$I_{g_2}$	...	3.3	mA
$g_m$	5.5	12	mA/V
$r_a$	...	> 350	k $\Omega$
$\mu$	17	...	

**B9A**

