

Trioda mocy

RE 134


Wzmacniacz mocy m.cz.

4-kołkowy

RE 134

$$U_{\dot{z}} = 4V$$

$$I_{\dot{z}} = 150mA$$



Wartości charakterystyczne i robocze

U_a	250	V
U_s	-17	V
I_a	12	mA
S_a	2	mA/V
K_a	9	V/V
ϱ_a	4,6	k Ω
R_k	1,5	k Ω
R_a	12	k Ω
P_a	0,65	W
$U_{s\sim}$	12	V

Wartości graniczne

$U_{a\max}$	250	V
$P_{a\max}$	3	W
$R_{s\max}$	1,5	M Ω

Pojemności

$C_{s/a}$	5	pF
-----------	---	----

TYPY PODOBNE

B 409, DL 11, KL 1, RE 114

